

ETSI EN 300328 V1.9.1: 2015 MEASUREMENT AND TEST REPORT

For

Shenzhen Fenda Technology Co., Ltd.

**Fenda Hi-Tech Park, Zhoushi Road, Shiyan Town, Baoan District,
Shenzhen City, Guangdong, China**

E.U.T.: 2.1 Computer Multimedia Speaker

Model Name: A140X, A140U, A140BT, A140F, A160X, A160BT, A140XF

Brand name: F&D

Report Number: NTC1504127E-1

Test Date(s): August 31, 2016 to September 22, 2016

Report Date(s): September 22, 2016

Prepared by

Dongguan Nore Testing Center Co., Ltd.

**Building D, Gaosheng Science & Technology Park, Zhouxi Longxi
Road, Nancheng District, Dongguan City, Guangdong Province, China**

Tel: +86-769-22022444

Fax: +86-769-22022799

Prepared By

Approved & Authorized Signer



Alina Guo / Engineer



Iori Fan / Authorized Signatory

Note: This test report is for the customer shown above and their specific product only. It may not be duplicated or used in part without prior written consent from Dongguan Nore Testing Center Co., Ltd. The test results referenced from this report are relevant only to the sample tested.

TABLE OF CONTENTS

1. GENERAL INFORMATION	4
PRODUCT DESCRIPTION FOR EQUIPMENT UNDER TEST	4
2. DESCRIPTION OF TEST MODES	7
3. TEST FREQUENCIES	7
4. OBJECTIVE	7
5. TEST METHODOLOGY	7
6. TEST FACILITY	8
7. MEASUREMENT UNCERTAINTY	8
8. SUPPORT EQUIPMENT	9
9. RF OUTPUT POWER	10
10. DWELL TIME, MINIMUM FREQUENCY OCCUPATION AND	12
HOPPING SEQUENCE	12
11. OCCUPIED CHANNEL BANDWIDTH	22
12. HOPPING FREQUENCY SEPARATION	26
13. TRANSMITTER UNWANTED EMISSIONS IN THE OUT-OF BAND DOMAIN	30
14. TRANSMITTER SPURIOUS EMISSIONS	33
15. RECEIVER SPURIOUS EMISSIONS	36
16. TEST EQUIPMENT LIST	38
APPENDIX I	39
INFORMATION AS REQUIRED BY EN 300 328 V1.9.1, CLAUSE 5.3.1	39
APPENDIX I	45
PHOTOGRPHS OF TEST SETUP	45

Revision History of This Test Report

Report Number	Description	Issued Date
NTC1504127E	Initial Issue	2015-05-13
NTC1504127E-1	Changed model number and updated the edition of the standard	2016-09-22

1. GENERAL INFORMATION

PRODUCT DESCRIPTION FOR EQUIPMENT UNDER TEST

Manufacturer	: F&D Technology (Shenzhen) Co., Ltd
Address	: Fenda Hi-Tech Park, Zhoushi Road, Shiyan Town, Baoan District, Shenzhen City, Guangdong, China
Factory	: F&D Technology (Shenzhen) Co., Ltd
Address	: Fenda Hi-Tech Park, Zhoushi Road, Shiyan Town, Baoan District, Shenzhen City, Guangdong, China
Product Name	: 2.1 Computer Multimedia Speaker
Model Name	: A140X, A140U, A140BT, A140F, A160X, A160BT, A140XF All tests were carried on model A140X.
Model Difference Description	: These models have the same circuitry, electrical mechanical, PCB layout and physical construction. Their differences in model number due to trading purpose.
Power Supply	: AC 220-240V 50/60Hz, 0.3A
Test Voltage	: AC 230V 50Hz
Operating Temperature Range	: 0°C to 35°C (Declaration by manufacturer)
Note	: <ol style="list-style-type: none">1. This report was an additional report based on original report NTC1504127E.2. Both of reports are the same. But this report has changed model number and updated the edition of the standard.3. The original model and new model are the same. Their difference in appearance.4. According this change, we have retest all items, details refer to the test report.

Technical Specification:

Bluetooth Version	: 2.1+EDR
Frequency Range	: 2402-2480MHz
Modulation Type	: GFSK, $\pi/4$ -DQPSK
Modulation Technology	: FHSS
Number of Channel	: 79
Channel Space	: 1MHz
Antenna Type	: PCB
Antenna Gain	: 0dBi (Declaration by manufacturer)
Max RF Output Power	: -4.62 dBm (E.I.R.P.)
Adaptive/Non-Adaptive Equipment	: Adaptive equipment

SUMMARY OF TEST RESULTS		
Section (ETSI EN 300328)	Description of Test	TEST RESULT
4.3.1.2 / 4.3.2.2	RF Output Power	Compliant
4.3.2.3	Power Spectral Density (Modulations other than FHSS equipment)	N/A
4.3.1.3 / 4.3.2.4	Duty cycle, Tx-Sequence, Tx-gap (Non-adaptive equipment)	N/A see note
4.3.1.4	Dwell time, Minimum Frequency Occupation & Hopping Sequence (FHSS equipment)	Compliant
4.3.1.5	Hopping Frequency Separation (FHSS equipment)	Compliant
4.3.1.6 / 4.3.2.5	Medium Utilisation (Non-adaptive equipment)	N/A see note
4.3.1.7 / 4.3.2.6	Adaptivity	N/A see note
4.3.1.8 / 4.3.2.7	Occupied Channel Bandwidth	Compliant
4.3.1.9 / 4.3.2.8	Transmitter unwanted emission in the OOB domain	Compliant
4.3.1.10 / 4.3.2.9	Transmitter unwanted emissions in the spurious domain	Compliant
4.3.1.11 / 4.3.2.10	Receiver spurious emissions	Compliant
4.3.1.12 / 4.3.2.11	Receiver Blocking	N/A see note

Note: These requirements do not apply for equipment with a maximum declared RF Output power of less than 10dBm EIRP or for equipment when operating in a mode where the RF Output power is less than 10dBm EIRP.

2. DESCRIPTION OF TEST MODES

The EUT has been tested under Normal Operating condition. Pre-defined engineering program for regulatory testing used to control the EUT for staying in continuous transmitting and receiving mode is programmed. All data rate and modulation type were tested, only the worst-case record in this report.

3. TEST FREQUENCIES

Channel	Frequency MHz
0	2402
39	2441
78	2480

Test Item	Software	Description
Conducted RF Testing and Radiated testing	FCCAssist_1.5	Set the EUT to different modulation and channel

4. OBJECTIVE

Electromagnetic compatibility and Radio spectrum Matters (ERM); Wideband Transmission systems; Data transmission equipment operating in the 2.4GHz ISM band and using wide band modulation techniques; Harmonized EN covering essential requirements under article 3.2 of the R&TTE Directive.

The objective is to determine compliance with ETSI EN 300328 V1.9.1 (2015-02).

5. TEST METHODOLOGY

All measurements contained in this report were conducted with ETSI EN 300328 V1.9.1 (2015-02).

6. TEST FACILITY

Site Description

EMC Lab : Listed by CNAS, August 14, 2015
The certificate is valid until August 13, 2018
The Laboratory has been assessed and proved to
be in compliance with CNAS/CL01
The Certificate Registration Number is L5795.

Listed by FCC, July 03, 2014
The Certificate Number is 665078.

Listed by Industry Canada, June 18, 2014
The Certificate Registration Number. Is 46405-9743

Name of Firm : Dongguan Nore Testing Center Co., Ltd.
(Dongguan NTC Co., Ltd.)
Site Location : Building D, Gaosheng Science & Technology Park,
Zhouxi Longxi Road, Nancheng District, Dongguan
City, Guangdong Province, China

7. MEASUREMENT UNCERTAINTY

Parameter	Uncertainty
Occupied Channel Bandwidth	$\pm 1.42 \times 10^{-4}\%$
RF output power, conducted	$\pm 1.06\text{dB}$
Power Spectral Density, conducted	$\pm 1.06\text{dB}$
Unwanted Emissions, conducted	$\pm 2.51\text{dB}$
All emissions, radiated	$\pm 3.70\text{dB}$
Temperature	$\pm 0.8^{\circ}\text{C}$
Humidity	$\pm 3.2\%$
DC and low frequency voltages	$\pm 0.1\%$
Time	$\pm 5\%$
Duty cycle	$\pm 5\%$

This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of $k=2$

8. SUPPORT EQUIPMENT

Notebook PC	: Manufacturer: IBM Corporation M/N: R50e S/N: L3-HZNGO P/N: 1834KDC
Adapter	: Manufacturer: IBM Corporation M/N: 08K8210 Input: AC100-240V 50/60Hz 0.5-1.0A Output: DC 16V 4.5A

9. RF OUTPUT POWER

Limits


Frequency Band	Limit
2400 ~ 2483.5 MHz	Equivalent isotropic radiated power (e.i.r.p.) ≤ 20 dBm

Test Method

1. Please refer to ETSI EN 300328 (V_{1.9.1}) clause 5.3.2.2.1 for conducted measurement method.
2. The measurements shall be performed at both normal environmental conditions and at The extremes of the operating temperature range.

Test Configuration

Temperature and Voltage Measurement



Test Result

Pass.

Please refer to following data tables.

GFSK				
Humidity :		52 %	Temperature :	22 °C
Test Result:		PASS	Test By:	Sance
Antenna Assembly Gain:			0dBi	
Cable Loss=			1.5dB	
Number of Burst			>20	
Hopping Mode				
Temperature (°C)	Voltage (V)	Reading dBm	EIRP dBm	Limit dBm
25	AC 230	-6.12	-4.62	20
0	AC 230	-6.34	-4.84	20
35	AC 230	-6.50	-5.00	20

Note: Calculated Power(dBm)=Output Power(dBm)+Cable Loss(dB)+Antenna Gain(dBi)

π/4-DQPSK				
Humidity :		52 %	Temperature :	
Test Result:		PASS	Test By:	
Antenna Assembly Gain:			0dBi	
Cable Loss=			1.5dB	
Number of Burst			>20	
Hopping Mode				
Temperature (°C)	Voltage (V)	Reading dBm	EIRP dBm	Limit dBm
25	AC 230	-6.65	-5.15	20
0	AC 230	-7.49	-5.99	20
35	AC 230	-7.33	-5.83	20

Note: Calculated Power(dBm)=Output Power(dBm)+Cable Loss(dB)+Antenna Gain(dBi)

10. DWELL TIME, MINIMUM FREQUENCY OCCUPATION AND HOPPING SEQUENCE

Limits

Dwell Time	
Test Condition	Limit
Non-adaptive frequency hopping systems	$\leq 15 \text{ ms}$
Adaptive frequency hopping systems	$\leq 400 \text{ ms}$

Minimum Frequency Occupation Time	
Test Condition	Limit
Non-adaptive frequency hopping systems	Equal to one dwell time within a period not exceeding four times the product of the dwell time per hop and the number of hopping frequencies in use.
Adaptive frequency hopping systems	

Hopping sequence(s)	
Test Condition	Limit
Non-adaptive frequency hopping systems	≥ 15 hopping frequencies or 15/minimum Hopping Frequency Separation in MHz , whichever is the greater.
Adaptive frequency hopping systems	Operating frequency band $\geq 58.45 \text{ MHz}$ (Operating over a minimum of 70 % of the operating in the band 2,4 GHz to 2,4835 GHz)
	≥ 15 hopping frequencies or 15/minimum Hopping Frequency Separation in MHz , whichever is the greater.

Test Method

1. Please refer to ETSI EN 300328 (V_{1.9.1}) clause 5.3.4.2.1 for conducted measurement method.
2. The measurements shall be performed at normal environmental condition.

Test Configuration



Test Result

Pass.

Please refer to following data tables and test plots.

Temperature :	22 °C	Humidity :	53%
Test Date :	September 07, 2016	Test Result:	PASS
Test By:	Sance		


Hopping Sequence				
Hopping Channels	Hopping Channels Limits	Min. Hopping Range (%)	Min. Hopping Range Limit(%)	Result
GFSK				
79	15	95.51	70.00%	PASS
$\pi/4$ -DQPSK				
79	15	95.91	70.00%	PASS

Dwell Time						
Mode	Number of Hopping Channel	Number of transmission in a period (channel number *0.4sec		Dwell Time	Limit (ms)	Result
		Period (Sec)	Sweep time (Sec)			
GFSK						
DH1	79	31.6	4	340.00	400	PASS
DH3	79	31.6	4	352.44	400	PASS
DH5	79	31.6	4	355.88	400	PASS
π/4-DQPSK						
DH1	79	31.6	4	45.88	400	PASS
DH3	79	31.6	4	246.24	400	PASS
DH5	79	31.6	4	307.09	400	PASS

Minimum Frequency Occupation				
Mode	Number of Hopping Channel	Number of transmission in a period of 4*Dwell time*number of hopping channel	Minimum Limit (ms)	Result (Pass/Fail)
GFSK				
DH1	79	7	≥ 1	PASS
DH3	79	1	≥ 1	PASS
DH5	79	1	≥ 1	PASS
$\pi/4$ -DQPSK				
DH1	79	2	≥ 1	PASS
DH3	79	2	≥ 1	PASS
DH5	79	6	≥ 1	PASS


GFSK DH1

Dwell Time



RBW: 500 KHz VBW: 2000 KHz Sweep Points: 30001


Minimum Frequency Occupation



RBW: 500 KHz VBW: 2000 KHz Sweep Points: 30001


GFSK DH3

Dwell Time



RBW: 500 KHz VBW: 2000 KHz Sweep Points: 30001


Minimum Frequency Occupation



RBW: 500 KHz VBW: 2000 KHz Sweep Points: 30001


GFSK DH5

Dwell Time





RBW: 500 KHz VBW: 2000 KHz Sweep Points: 30001

Minimum Frequency Occupation





RBW: 500 KHz VBW: 2000 KHz Sweep Points: 30001



$\pi/4$ -DQPSK DH1




$\pi/4$ -DQPSK DH3




$\pi/4$ -DQPSK DH5



Hopping Sequence GFSK



$\pi/4$ -DQPSK



11. OCCUPIED CHANNEL BANDWIDTH

Limits

Condition	Limit
All types of equipment	Shall fall completely within the band 2400 to 2483.5 MHz
For non-adaptive using wide band modulations other than FHSS system and e.i.r.p > 10dBm	Less than 20MHz
For non-adaptive Frequency Hopping system and e.i.r.p > 10dBm	Less than 5MHz

Test Method

1. Please refer to ETSI EN 300328 (V_{1.9.1}) clause 5.3.8.2.1 for conducted measurement method.
2. The measurements shall be performed at normal environmental condition.

Test Configuration



Test Result

Pass.

Please refer to following data tables and test plots.


Temperature : 22 °C Humidity : 53%
Test Date : September 07, 2016 Test Result: PASS
Test By: Sance

Channel frequency (MHz)	99% Bandwidth (KHz)	FL at 99% BW (MHz)	FH at 99% BW (MHz)	Limit	Result
GFSK					
2402	830	2401.47	2402.30	FL > 2.4 GHz and FH < 2.4835 GHz	Pass
2480	830	2479.46	2480.30		Pass
π/4-DQPSK					
2402	1170	2401.30	2402.48	FL > 2.4 GHz and FH < 2.4835 GHz	Pass
2480	1170	2479.29	2480.47		Pass

Note: FL is the lowest frequency of the 99% occupied bandwidth of power envelope.
FH is the highest frequency of the 99% occupied bandwidth of power envelope.


GFSK Lowest Channel

Occupied Channel Bandwidth




GFSK Highest Channel


Occupied Channel Bandwidth



$\pi/4$ -DQPSK Lowest Channel



$\pi/4$ -DQPSK Highest Channel



12. HOPPING FREQUENCY SEPARATION

Limits

Condition	Limit
Nom-adaptive frequency hopping systems	The minimum Hopping Frequency Separation shall be equal to Occupied Channel Bandwidth of a single hop, with a minimum separation of 100 kHz.
Adaptive frequency hopping systems	The minimum Hopping Frequency Separation shall be 100 kHz.

Test Method

1. Please refer to ETSI EN 300328 (V_{1.9.1}) clause 5.3.5.2.1 for conducted measurement method.
2. The measurements shall be performed at normal environmental condition.

Test Configuration



Test Result

Pass.


Please refer to following data tables and test plots.

Temperature : 22 °C Humidity : 53%
Test Date : September 07, 2016 Test Result: PASS
Test By: Sance

Channel frequency (MHz)	Channel Separation (KHz)	Limit (MHz) Minimum	Result
GFSK			
2402	1000	0.1	Pass
2480	1000	0.1	Pass
$\pi/4$ -DQPSK			
2402	1150	0.1	Pass
2480	1000	0.1	Pass


GFSK Lowest Channel

Hopping Frequency Separation




GFSK Highest Channel

Hopping Frequency Separation




$\pi/4$ -DQPSK

Hopping Frequency Separation



$\pi/4$ -DQPSK

Hopping Frequency Separation




13. TRANSMITTER UNWANTED EMISSIONS IN THE OUT-OF-BAND DOMAIN

Limits

The transmitter unwanted emissions in the out-of-band domain but outside the allocated band, shall not exceed the values provided by the mask

Transmit mask




Test Method

1. Please refer to ETSI EN 300328 (V_{1.9.1}) clause 5.3.9.2.1 for conducted measurement method.
2. The measurements shall be performed at both normal environmental conditions and at The extremes of the operating temperature range.

Test Configuration

Temperature and Voltage Measurement



Test Result

Pass.

Please refer to following data tables.

Temperature : 22 °C Humidity : 53%
Test Date : September 07, 2016 Test Result: PASS
Test By: Sance

Condition		2400-BW~2400 / 2483.5+BW ~2483.5 (dBm/MHz)	Limit (dBm/MHz)	2400-2*BW~2400-BW / 2483.5+2*BW ~2483.5+BW (dBm/MHz)	Limit (dBm/MHz)	Result
Temperature (°C)	Voltage V					
GFSK (2402MHz)						
25	AC230	-39.044	-10	-47.454	-20	PASS
0	AC230	-39.048	-10	-47.459	-20	PASS
35	AC230	-39.126	-10	-47.654	-20	PASS
GFSK (2480MHz)						
25	AC230	-57.894	-10	-61.294	-20	PASS
0	AC230	-57.896	-10	-61.296	-20	PASS
35	AC230	-57.913	-10	-61.299	-20	PASS
π/4-DQPSK (2402MHz)						
25	AC230	-38.824	-10	-46.144	-20	PASS
0	AC230	-38.829	-10	-46.241	-20	PASS
35	AC230	-38.834	-10	-46.239	-20	PASS
π/4-DQPSK (2480MHz)						
25	AC230	-58.654	-10	-61.414	-20	PASS
0	AC230	-58.659	-10	-61.418	-20	PASS
35	AC230	-58.667	-10	-61.526	-20	PASS

14. TRANSMITTER SPURIOUS EMISSIONS

Limits:

The transmitter unwanted emissions in the spurious domain shall not exceed the values.


Frequency Range	Maximum power e.r.p. (≤ 1 GHz) e.i.r.p. (> 1 GHz)	Bandwidth
30 MHz to 47MHz	-36 dBm	100KHz
47 MHz to 74MHz	-54 dBm	100KHz
74 MHz to 87.5MHz	-36 dBm	100KHz
87.5 MHz to 118MHz	-54 dBm	100KHz
118 MHz to 174MHz	-36 dBm	100KHz
174 MHz to 230MHz	-54 dBm	100KHz
230 MHz to 470MHz	-36 dBm	100KHz
470 MHz to 862MHz	-54 dBm	100KHz
862 MHz to 1GHz	-36 dBm	100KHz
1GHz to 12.75GHz	-30 dBm	1MHz

Test Method


1. Please refer to ETSI EN 300328 (V_{1.9.1}) clause 5.3.10.2.2 for radiated measurement method.
2. The measurements shall be performed at normal environmental condition.

Test Configuration

Below 1GHz



Above 1GHz



Test Result

Pass.

Please refer to following data tables (The worst case GFSK)

Below 1GHz Hopping				
Humidity : 54 %		Temperature : 22 °C		
Test Result: PASS		Test By: Sance		
Test Mode: TX				
Frequency (MHz)	Antenna Polarization	Emission level (dBm)	Limit (dBm)	Margin (dB)
480.0799	Vertical	-63.99	-54.00	-9.99
512.0900	Vertical	-64.65	-54.00	-10.65

576.1100	Horizontal	-61.61	-54.00	-7.61
640.1299	Horizontal	-60.13	-54.00	-6.13
768.1698	Horizontal	-60.01	-54.00	-6.01

Above 1GHz Hopping				
Humidity : 54 %		Temperature : 22 °C		
Test Result: PASS		Test By: Sance		
Test Mode: TX				
Frequency (MHz)	Antenna Polarization	Emission level (dBm)	Limit (dBm)	Margin (dB)
4804	Vertical	-45.13	-30	-15.13
7206	Vertical	-42.61	-30	-12.61

4804	Horizontal	-45.71	-30	-15.71
7206	Horizontal	-42.36	-30	-12.36

- Note:**
1. Emission Level (dBm) = Reading level (dBm)+Correction Factor (dB)
 2. Data of measurement within this frequency range shown “ --- ” in the table above means the reading of emissions are attenuated more than 10dB below the permissible limits.
 3. The Test frequency range is 30MHz to12.75GHz.

15. RECEIVER SPURIOUS EMISSIONS

Limits

Frequency Range	Maximum power e.r.p. (≤ 1 GHz) e.i.r.p. (> 1 GHz)	Bandwidth
30 MHz to 1GHz	-57 dBm	100KHz
1GHz to 12.75GHz	-47 dBm	1MHz

Test Method

1. Please refer to ETSI EN 300328 (V_{1.9.1}) clause 5.3.11.2.2 for radiated measurement method.
2. The measurements shall be performed at normal environmental condition.

Test Configuration

Same as section 14 in this test report.

Test Result

Pass.

Please refer to following data tables (the worst case GFSK).

Below 1GHz Hopping				
Humidity : 54 %		Temperature : 22 °C		
Test Result: PASS		Test By: Sance		
Test Mode: RX				
Frequency (MHz)	Antenna Polarization	Emission level (dBm)	Limit (dBm)	Margin (dB)
512.0900	Vertical	-64.39	-57.00	-7.39
640.1300	Vertical	-63.65	-57.00	-6.65

576.1100	Horizontal	-62.28	-57.00	-5.28
640.1299	Horizontal	-61.16	-57.00	-4.16
768.1698	Horizontal	-61.03	-57.00	-4.03
--				

Above 1GHz Hopping				
Humidity : 50 %		Temperature : 23 °C		
Test Result: PASS		Test By: Sance		
Test Mode: RX				
Frequency (MHz)	Antenna Polarization	Emission level (dBm)	Limit (dBm)	Margin (dB)
4804	Vertical	-54.34	-47	-7.34
7206	Vertical	-50.56	-47	-3.56

4804	Horizontal	-56.78	-47	-9.78
7206	Horizontal	-52.69	-47	-5.69

- Note:**
1. Emission Level (dBm) = Reading level (dBm)+Correction Factor (dB)
 2. Data of measurement within this frequency range shown “ --- ” in the table above means the reading of emissions are attenuated more than 10dB below the permissible limits.
 3. The Test frequency range is 30MHz to12.75GHz.

16. TEST EQUIPMENT LIST

Description	Manufacturer	Model Number	Serial Number	Calibration Date	Calibration Due Date
Receiver	Rohde & Schwarz	ESCI7	100837	Mar. 07, 2016	Mar. 07, 2017
DC Power Source	HUA YI	HY5003-2	N/A	Nov.03, 2015	Nov.02, 2016
Temperature & Humidity Chamber	HAIDA	DH-225T	N/A	Nov.05, 2015	Nov.04, 2016
Spectrum Analyzer	Rohde & Schwarz	FSU26	200409/026	Mar. 07, 2016	Mar. 07, 2017
Horn Antenna	COM-Power	AH-118	071078	Mar. 07, 2016	Mar. 07, 2017
Pre-Amplifier	COM-Power	PAM-118	443007	Mar. 07, 2016	Mar. 07, 2017
Broadband Antenna	Schwarzbeck	VULB9162	9162-010	Apr. 25, 2016	Apr. 25, 2017
Pre-Amplifier	Agilent	8449B	3008A02964	Mar. 07, 2016	Mar. 07, 2017
Pre-Amplifier	HP	HP 8447D	1145A00203	Mar. 07, 2016	Mar. 07, 2017
Power Sensor	DARE	RPR3006 W	15I00041SN O64	Mar. 07, 2016	Mar. 06, 2017
Test Software	Acentest	AT890-SW	N/A	N/A	N/A

APPENDIX I

INFORMATION AS REQUIRED BY EN 300 328 V1.9.1, CLAUSE 5.3.1

In accordance with EN 300 328, clause 5.3.1, the following information is provided by the supplier.

a) The type of modulation used by the equipment:	<input checked="" type="checkbox"/> FHSS <input type="checkbox"/> other forms of modulation
b) In case of FHSS modulation:	<ul style="list-style-type: none"> In case of non-Adaptive Frequency Hopping equipment: The number of Hopping Frequencies: _____ In case of Adaptive Frequency Hopping Equipment: The maximum number of Hopping Frequencies: <u>79</u> The minimum number of Hopping Frequencies: _____ The (Average) Dwell Time: <u>323.545ms</u>
c) Adaptive / non-adaptive equipment:	<input type="checkbox"/> non-adaptive Equipment <input checked="" type="checkbox"/> adaptive Equipment without the possibility to switch to a non-adaptive mode <input type="checkbox"/> adaptive Equipment which can also operate in a non-adaptive mode
d) In case of adaptive equipment:	The Channel Occupancy Time implemented by the equipment: _____ ms <input checked="" type="checkbox"/> The equipment has implemented an LBT based DAA mechanism <ul style="list-style-type: none"> In case of equipment using modulation different from FHSS: <input type="checkbox"/> The equipment is Frame Based equipment <input type="checkbox"/> The equipment is Load Based equipment <input type="checkbox"/> The equipment can switch dynamically between Frame Based and Load Based equipment The CCA time implemented by the equipment: _____ μ s <input type="checkbox"/> The equipment has implemented an non-LBT based DAA mechanism <input type="checkbox"/> The equipment can operate in more than one adaptive mode
e) In case of non-adaptive Equipment:	The maximum RF Output Power (e.i.r.p.): _____ dBm The maximum (corresponding) Duty Cycle: _____ % Equipment with dynamic behaviour, that behaviour is described here. (e.g. the different combinations of duty cycle and orresponding power levels to be declared):
f) The worst case operational mode for each of the following tests:	<ul style="list-style-type: none"> RF Output Power <u>GFSK</u> Power Spectral Density <u>N/A</u> Duty cycle, Tx-Sequence, Tx-gap <u>N/A</u> Accumulated Transmit time, Frequency Occupation & Hopping Sequence (only for FHSS equipment) <u>GFSK</u> Hopping Frequency Separation (only for FHSS equipment) <u>$\pi/4$-DQPSK</u> Medium Utilisation <u>N/A</u> Adaptivity & Receiver Blocking <u>N/A</u> Nominal Channel Bandwidth <u>$\pi/4$-DQPSK</u> Transmitter unwanted emissions in the OOB domain <u>GFSK</u> Transmitter unwanted emissions in the spurious domain <u>GFSK</u> Receiver spurious emissions <u>GFSK</u>

<p>g) The different transmit operating modes (tick all that apply):</p>	<p><input checked="" type="checkbox"/> Operating mode 1: Single Antenna Equipment</p> <p><input checked="" type="checkbox"/> Equipment with only 1 antenna</p> <p><input type="checkbox"/> Equipment with 2 diversity antennas but only 1 antenna active at any moment in time</p> <p><input type="checkbox"/> Smart Antenna Systems with 2 or more antennas, but operating in a (legacy) mode where only 1 antenna is used. (e.g. IEEE 802.11™ [i.3] legacy mode in smart antenna systems)</p> <hr/> <p><input type="checkbox"/> Operating mode 2: Smart Antenna Systems - Multiple Antennas without beam forming</p> <p><input type="checkbox"/> Single spatial stream / Standard throughput / (e.g. IEEE 802.11™ [i.3] legacy mode)</p> <p><input type="checkbox"/> High Throughput (> 1 spatial stream) using Occupied Channel Bandwidth 1</p> <p><input type="checkbox"/> High Throughput (> 1 spatial stream) using Occupied Channel Bandwidth 2</p> <p>NOTE: Add more lines if more channel bandwidths are supported.</p> <hr/> <p><input type="checkbox"/> Operating mode 3: Smart Antenna Systems - Multiple Antennas with beam forming</p> <p><input type="checkbox"/> Single spatial stream / Standard throughput / (e.g. IEEE 802.11™ [i.3] legacy mode)</p> <p><input type="checkbox"/> High Throughput (> 1 spatial stream) using Occupied Channel Bandwidth 1</p> <p><input type="checkbox"/> High Throughput (> 1 spatial stream) using Occupied Channel Bandwidth 2</p> <p>NOTE: Add more lines if more channel bandwidths are supported.</p>
<p>h) In case of Smart Antenna Systems:</p>	<p>•The number of Receive chains: _____</p> <hr/> <p>•The number of Transmit chains: _____</p> <p><input type="checkbox"/> symmetrical power distribution</p> <p><input type="checkbox"/> asymmetrical power distribution</p> <hr/> <p>In case of beam forming, the maximum beam forming gain: _____</p> <p>NOTE: Beam forming gain does not include the basic gain of a single antenna.</p>
<p>i) Operating Frequency Range(s) of the equipment:</p>	<p>•Operating Frequency Range 1: <u>2402</u> MHz to <u>2480</u> MHz</p> <p>•Operating Frequency Range 2: _____ MHz to _____ MHz</p> <p>NOTE: Add more lines if more Frequency Ranges are supported.</p>
<p>j) Occupied Channel Bandwidth(s):</p>	<p>•Nominal Channel Bandwidth 1: <u>830</u> KHz</p> <p>•Nominal Channel Bandwidth 2: <u>1170</u> KHz</p> <p>NOTE: Add more lines if more channel bandwidths are supported.</p>
<p>k) Type of Equipment (stand-alone, combined, plug-in radio device, etc.): Stand-alone</p>	<p><input checked="" type="checkbox"/> Stand-alone</p> <p><input type="checkbox"/> Combined Equipment (Equipment where the radio part is fully integrated within another type of equipment)</p> <p><input type="checkbox"/> Plug-in radio device (Equipment intended for a variety of host systems)</p> <p><input type="checkbox"/> Other _____</p>

l) The extreme operating conditions that apply to the equipment:	Operating temperature range: <u> 0 </u> ° C to <u> 35 </u> ° C Details provided are for the: <input checked="" type="checkbox"/> stand-alone equipment <input type="checkbox"/> combined (or host) equipment <input type="checkbox"/> test jig																																								
m) The intended combination(s) of the radio equipment power settings and one or more antenna assemblies and their corresponding e.i.r.p levels:	<div> •Antenna Type: <input checked="" type="checkbox"/> PCB Antenna: Antenna Gain: <u> 0 </u> dBi If applicable, additional beamforming gain (excluding basic antenna gain): <u> </u> dB <input type="checkbox"/> Temporary RF connector provided <input type="checkbox"/> No temporary RF connector provided </div> <div> <input type="checkbox"/> Dedicated Antennas (equipment with antenna connector) <input type="checkbox"/> Single power level with corresponding antenna(s) <input type="checkbox"/> Multiple power settings and corresponding antenna(s) Number of different Power Levels: <u> </u> Power Level 1: <u> </u> dBm Power Level 2: <u> </u> dBm Power Level 3: <u> </u> dBm NOTE 1: Add more lines in case the equipment has more power levels. NOTE 2: These power levels are conducted power levels (at antenna connector). • For each of the Power Levels, provide the intended antenna assemblies, their corresponding gains (G) and the resulting e.i.r.p. levels also taking into account the beamforming gain (Y) if applicable Power Level 1: <u> </u> Number of antenna assemblies provided for this power level: <table border="1" style="width: 100%; border-collapse: collapse; text-align: center;"> <thead> <tr> <th style="width: 15%;">Assembly #</th> <th style="width: 20%;">Gain (dBi)</th> <th style="width: 20%;">e.i.r.p.(dBm)</th> <th style="width: 45%;">Part number or model name</th> </tr> </thead> <tbody> <tr><td>1</td><td></td><td></td><td></td></tr> <tr><td>2</td><td></td><td></td><td></td></tr> <tr><td>3</td><td></td><td></td><td></td></tr> <tr><td>4</td><td></td><td></td><td></td></tr> </tbody> </table> Note: Add more rows in case more antenna assemblies are supported for this power level. Power Level 2: <u> </u> Number of antenna assemblies provided for this power level: <table border="1" style="width: 100%; border-collapse: collapse; text-align: center;"> <thead> <tr> <th style="width: 15%;">Assembly #</th> <th style="width: 20%;">Gain (dBi)</th> <th style="width: 20%;">e.i.r.p.(dBm)</th> <th style="width: 45%;">Part number or model name</th> </tr> </thead> <tbody> <tr><td>1</td><td></td><td></td><td></td></tr> <tr><td>2</td><td></td><td></td><td></td></tr> <tr><td>3</td><td></td><td></td><td></td></tr> <tr><td>4</td><td></td><td></td><td></td></tr> </tbody> </table> Note: Add more rows in case more antenna assemblies are supported for this power level. </div>	Assembly #	Gain (dBi)	e.i.r.p.(dBm)	Part number or model name	1				2				3				4				Assembly #	Gain (dBi)	e.i.r.p.(dBm)	Part number or model name	1				2				3				4			
Assembly #	Gain (dBi)	e.i.r.p.(dBm)	Part number or model name																																						
1																																									
2																																									
3																																									
4																																									
Assembly #	Gain (dBi)	e.i.r.p.(dBm)	Part number or model name																																						
1																																									
2																																									
3																																									
4																																									


	<p>Power Level 3: _____</p> <p>Number of antenna assemblies provided for this power level:</p> <table border="1" data-bbox="526 320 1420 533"> <thead> <tr> <th>Assembly #</th><th>Gain (dBi)</th><th>e.i.r.p.(dBm)</th><th>Part number or model name</th></tr> </thead> <tbody> <tr><td>1</td><td></td><td></td><td></td></tr> <tr><td>2</td><td></td><td></td><td></td></tr> <tr><td>3</td><td></td><td></td><td></td></tr> <tr><td>4</td><td></td><td></td><td></td></tr> </tbody> </table> <p>Note: Add more rows in case more antenna assemblies are supported for this power level.</p>	Assembly #	Gain (dBi)	e.i.r.p.(dBm)	Part number or model name	1				2				3				4			
Assembly #	Gain (dBi)	e.i.r.p.(dBm)	Part number or model name																		
1																					
2																					
3																					
4																					
<p>n) The nominal voltages of the stand-alone radio equipment or the nominal voltages of the combined (host) equipment or test jig in case of plug-in devices:</p>	<p>Details provided are for the: <input checked="" type="checkbox"/> stand-alone equipment <input type="checkbox"/> combined (or host) equipment <input type="checkbox"/> test jig</p> <p>Supply Voltage <input checked="" type="checkbox"/> AC mains State AC voltage <u>230</u> V <input type="checkbox"/> DC State DC voltage _____</p> <p>In case of DC, indicate the type of power source</p> <p><input type="checkbox"/> Internal Power Supply <input type="checkbox"/> External Power Supply or AC/DC adapter <input type="checkbox"/> Battery <input type="checkbox"/> Other: _____</p>																				
<p>o) Describe the test modes available which can facilitate testing:</p>	<p>The EUT provides TX Mode to control RF signal transmission</p>																				
<p>p) The equipment type (e.g. Bluetooth®, IEEE 802.11™ [i.3], proprietary, etc.):</p>	<p>Bluetooth®</p>																				
<p>q) If applicable, the statistical analysis referred to in clause 5.3.1 q)</p>	<p>(to be provided as separate attachment)</p>																				
<p>r) If applicable, the statistical analysis referred to in clause 5.3.1 r)</p>	<p>(to be provided as separate attachment)</p>																				
<p>s) Geo-location capability supported by the equipment:</p>	<p><input type="checkbox"/> Yes <input type="checkbox"/> The geographical location determined by the equipment as defined in clause 4.3.1.13.2 or clause 4.3.2.12.2 is not accessible to the user. <input type="checkbox"/> No</p>																				

Page 44 of 46

APPENDIX I

PHOTOGRPHS OF TEST SETUP

Radiated Emission Below 1 GHz



Radiated Emission Above 1 GHz



--- End ---